

Veriton | Z

Z2660G

Great flexibility, better efficiency

- Ergonomic viewing and placement options
 - Frame stand tilts from 8° to 60°
 - Optional Acer ErgoStand tilts from -5° to 35°
 - VESA wall mount supported
- Full HD webcam can rotate up to 180°
- Screwless design, modular components



Acer recommends Windows 8.

Veriton Z2660G

SPECIFICATIONS


Front view, with frame stand



Rear view, with optional ErgoStand



Bottom view



Product views

1	HD microphone	11	19.5" LED-backlit LCD (touch optional)	21	VESA mounting holes
2	Optical drive (optional)	12	Internet/optical drive indicator light	22	Adjustable ErgoStand (optional)
3	Audio-in jack	13	Power indicator light	23	DC-in power jack
4	Tiltable frame stand (6°-60°)	14	Power button	24	Ethernet port
5	Audio-out jack	15	Monitor on/off button	25	USB 3.0 port (optional, supports charging)
6	SD card reader (optional)	16	Brightness button	26	VGA port
7	USB 3.0 port (optional)	17	One-button recovery (OBR) pinhole	27	Serial port (optional)
8	Removable feet for stand	18	Rear view of rotating HD webcam	28	Combo stereo headphone/mic jack
9	Two HD speakers	19	Dust-proof intake hole of fan	29	Two USB 2.0 ports
10	Rotating webcam (180°) with indicator light	20	Ventilation hole	30	DisplayPort™ port

Operating system^{1,2}

Windows 8.1 Pro 64-bit	Windows 7 Professional 64-bit Service Pack 1
------------------------	--

CPU^{1,3}

CPU Intel Core i3 4150T LGA 3.0G 3M 1600 1150 35W Haswell

Chipset

Intel® H81 Express chipset – Intel Hd Graphics

Memory^{1,4,5}

4GB Up to 16 GB of dual-channel DDR3

Display¹

19.5" LED-backlit LCD 16:9 aspect ratio 1600 x 900 max resolution 250-nit brightness (cd/m²)

Storage^{1,6}

500GB

Optical drive (optional)

SuperMulti

Audio

Built-in stereo speakers Integrated high-definition sound

Webcam

Video conferencing: Integrated 2.0 MP Full HD high-sense webcam

Networking

Gigabit Ethernet 802.11a/b/g/n wireless LAN

Input and output

Front/side I/O connectors: Card reader, two audio jacks, USB 3.0 port
Rear I/O connectors: VGA port, DisplayPort™ port, serial port on board header (COM2), Ethernet port, combo stereo headphone/mic jack, two USB 2.0 ports, USB 3.0 port

Expansion slots

One PCIe x1 slot One Mini PCI Express® slot One mSata slot

Windows Store Apps^{7,8}

Productivity <ul style="list-style-type: none">• Evernote®	Utilities <ul style="list-style-type: none">• Acer Explorer v1.0
---	---

Windows Desktop Apps^{7,10}

Content <ul style="list-style-type: none">• Microsoft Office 2013¹¹ ISP & Communications <ul style="list-style-type: none">• Skype Multimedia <ul style="list-style-type: none">• Cyberlink® PowerDVD™• Cyberlink® YouCam¹²• Nero BackItUp 12 Essentials Operating System <ul style="list-style-type: none">• Microsoft Windows Virtual PC¹³• Microsoft Windows XP Mode¹³	Productivity <ul style="list-style-type: none">• PowerSaver^{9,10}• SmartBoot• Veriton ControlCenter• Evernote®• NewsXpresso⁹ Search <ul style="list-style-type: none">• Yahoo Search⁸ Security <ul style="list-style-type: none">• Acer Proshield• McAfee® Internet Security Suite¹⁰	<ul style="list-style-type: none">• McAfee® LiveSafe Internet Security Suite^{8,10}• Norton™ Online Backup Utilities <ul style="list-style-type: none">• Acer Identity Card• Acer Office Manager Agent• Acer Office Manager Console• Acer Registration• Acer Live Updater• Acer Recovery Management• Acer eSettings Management• Acer Screen Grasp^{8,14}	<ul style="list-style-type: none">• Acer Touch Tools^{8,14}• Agoda Weblink^{7,8}• Hotkey Utility v3.0• Software Assembler• Adobe Flash Player⁹• Adobe Reader X⁹• Power Management⁸• Yandex.Disk^{7,8} Web links <ul style="list-style-type: none">• Acer Accessory Store⁷
--	--	---	---

Commercial features

Intrusion alert (via BIOS) ¹ One-button recovery (OBR)	Hard drive password protection (via BIOS) PXE (Preboot eXecution Environment)	TPM v1.2 (Trusted Platform Module) ¹ WOL (Wake On Lan)
--	--	--

Commercial options

TPM v1.2 (Trusted Platform Module)	Internal speaker
------------------------------------	------------------

Optional accessories

	USB keyboard and mouse
--	------------------------

Power supply/adaptor

3-pin 90 W AC adapter

Dimensions

330 (W) x 60 (D) x 490 (H) mm (12.99 x 2.36 x 19.29 inches)

System compliance

DMI, GS, ENERGY STAR®, PC2001, RoHS

Certifications

BSMI, CCC, CE, FCC, CB

- Specifications vary depending on model.
- 64-bit software is required to enjoy the advantages of 64-bit processing.
- Only supports 35W CPU.
- A 64-bit operating system is required to enjoy the ultimate performance of 4 GB or higher memory.
- Memory speed may vary, depending on the CPU, chipset or memory fitted.
- 1 GB is 1 billion bytes. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Recovery Management uses a portion of the stated hard disk capacity as dedicated backup space.
- Bundled software may vary depending on hardware configuration, OS and regional availability.
- For Windows 8.1 only.
- For Windows 7 only.
- Trial periods vary depending on the geographic region and specifications: 365-day trial for China, Taiwan, Hong Kong and Singapore (Simplified Chinese and Traditional Chinese OS models); 60-day trial for other regions. The trial periods vary depending on the OS language: 365 days for Simple Chinese/Traditional Chinese/T.C. (Hong Kong); 60 days for others.
- Trial version.
- Optional.
- For Windows 7 Professional only.
- For touch model only.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty. In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region. Microsoft and Windows are registered trademarks of Microsoft Corporation. Intel, Intel Core, Core Inside, Pentium, and Pentium Inside are trademarks of Intel Corporation in the U.S. and other countries.

© 2013. All rights reserved. Acer Inc.